#### **Features**

- Low frequency in small size SMD
- Seam sealed ceramic package offers excellent environmental & heat resistance
- Extended temperature -40 to +85°C for industrial applications

## **Applications**

- Commercial and Industrial applications
- Wireless communications
- PDA and Smartphone
- Time of day applications



General Specifications		
Nominal Frequency	32.768kHz	
Frequency Tolerance at 25°C	±20ppm	
Temperature Coefficient	-0.034 ± 0.008ppm/Δ °C <sup>2</sup>	
Temperature Range (Operating)	-40 to $+85^{\circ}C$ (-40 to $+125^{\circ}C$ available)	
Storage Temperature	-55 to +125°C	
Load Capacitance $C_L$	6pF, 7pF, 9pF, 12.5pF	
Shunt Capacitance $C_0$	1.2pF typ.	
Motional Capacitance C <sub>1</sub>	3.7fF typ.	
Equivalent Series Resistance (ESR)	50KΩ typ. / 70KΩ max.	
Drive Level	1µW max.	
Aging per Year	±3ppm max.	
Insulation Resistance (M $\Omega$ )	500 at 100Vdc ±15Vdc	





#### x3.2 S

Part Numbering Guide								
Qantek Code	Package	Nominal Frequency (in kHz)	Load Capacitance	Operating Temperature Range	Frequency Tolerance	Packaging		
Q = Qantek	TC3 = 1.5x3.2 SMD Tuning Fork	32.768	06 = 6pF 07 = 7pF 09 = 9pF <b>12 = 12.5pF</b>	<b>B</b> = -40 to +85°C D = -40 to +125°C	1 = ±10ppm <b>2 = ±20ppm</b> 3 = ±30ppm	R = 3000pcs Tape&Reel		
Evample: OTC222 76912P2D bold latters - recommanded standard enactification								

Example: QTC332.76812B2R

## **Tape and Reel Dimensions**



#### Marking Code Guide

Contains manufacturer code / lot code



# **QANTEK Technology Corporation**

 Phone:
 +1 877-227-0440 (tollfree)

 Fax:
 +1 877-227-0440 (tollfree)

www.qantek.com info@qantek.com





## Frequency vs. Temperature Characteristics



For calculate the frequency stability the parabolic curvature constant (K) is needed For calculating the stability at 45°C?

- 1- Change in temperature ( $\Delta$ T) is (45-25) = +20°C
- 2- Change in frequency is  $(-0.034 \text{ x} (\Delta^{\circ}\text{C})^2) = (-0.034 \text{ x} (20)^2 = -13.6 \text{ppm}$



# QANTEK Technology Corporation Phone: +1 877-227-0440 (tollfree) Fax: +1 877-227-0440 (tollfree)

www.qantek.com info@qantek.com